ORDER NO. MD0503061S3

DVD Stereo System

SA-VK91DGC / SA-VK91DGS / SA-VK91DGCS / SA-VK91DGCP

Colour

(S) .... Silver Type

Additional information (Self-Diagnostic Function)

Please use this service manual together with the service manual for Model No. [SA-VK91DGC/GS-S, Order No. MD0407367C3], [SA-VK91DGCS/GCPS, Order No. MD0407366C3]

© 2005 Panasonic AVC Networks Singapore Pte. Ltd. All rights reserved. Unauthorized copying and distribution is a violation of law.

PDF created with pdfFactory Pro trial version www.pdffactory.com

Panasonic

1. Self-Diagnostic Display Function (Additional)

1.1. Doctor Mode set up

1. Turn on power for unit.
2. Select DVD/CD Mode. Ensure no disc is inserted in the unit.
3. Press & hold [STOP] button on main unit for at least 3 seconds, follow by [SUPER SURROUND] button on the main unit. It enters into doctor mode.
4. Press [POWER] button on main unit or remote control to exit doctor mode.

1.2. CR16 Mechanism Ageing Mode (Additional)

To perform the ageing mode :

1. Enter into doctor mode. (Refer to section 1.1 as mention above)
2. Press [3] button on remote control. It enters into ageing mode. (See below for ageing process)

Ageing process: -

1. Tray 1 open.
2. It waits for one second (Note : Do not put any disc into the tray)
3. Tray 1 close.

PDF created with pdfFactory Pro trial version www.pdffactory.com

4. TOC READ (Reading incomplete)

5. Tray 2 open & repeat process 1 to 4. (Process repeat until Tray 5)

6. Tray check.

7. Whole process complete (Counter on FL increase by 1)

Note : To exit ageing mode, press [POWER] button. The unit will power down. Do not unplug the power cord until FL display shows " GOODBYE ". This is to avoid tray jam problem.

Display Example :	**[0 0 0 0 0 T 3 O P]**	**...TRAY OPEN**
	[0 0 0 0 0 T 3 C L]	**...TRAY CLOSE**
	[0 0 0 0 0 T 3 R E]	**...TOC READING**
	[0 0 0 0 0 T 3 C H]	**...TRAY CHANGING**

M0411 M

PDF created with pdfFactory Pro trial version www.pdffactory.com